

L-QR1356MF

QR Code & 13.56MHz Mifare Card Reader

General Description

L-QR1356MF is dual technology reader in a single physical access control reader. It can read 1D / 2D QR code and CSN from 13.56MHz Mifare RFID credential. It has a Wiegand output to interface with access control and capable of sending 26/34-bit output.

Technical Specification

QR Code Reader

Size: 8mm – 100mm
Direction: up to 45°
Speed: < 200ms
Distance: up to 20cm

RFID Reader

HF: 13.56MHz Mifare CSN

Interface

26/34-bit Wiegand Output

Dimension

86mm (L) x 86mm (W) x 42mm (D)

Material

Polycarbonate and Tempered glass

Power Supply

DC 4-15V, 0.8A

